



The APart TLG-PRG50 is a 5+1 program selector (Ref; TLG-PRG6) combined with a 50 watt 100 Volt volume control (Ref; TLG-VOL50).

The TLG-PRG50 is equipped with a 24 Volt priority relais. This way a microphone call or emergency message will come through, even if the program selector or the volume control are in the "zero" position.

The TLG-PRG50 is build in a 7 module bTicino chassis of the Living series. The unit is supplied with a 7 module frame, without the cover plate.

TECHNICAL SPECIFICATIONS

Type	BTicino Living
Programs	5 + Priority
Attenuation steps	11 + 0
Handling power	50 watt
Voltage	100 Volt
24V priority	Yes
Build-in box	T-7MODINW (for brick walls)
Dimensions (H x W x D)	71 x 200 x 68 mm
Weight	0.37 Kg
colour	Dark grey